

# Safety isolating transformer VR 7,5/1/18



Picture shows VR 7,5/2/9

## Advantages

Minimum size at high output

Also with double output voltage for series or parallel connection

Permanent corrosion protection, high insulation value and maximum electrical reliability due to XtraDenseFill resin encapsulation


Self-extinguishing potting material

Space saving installation due to additional screw mounting in the base plate

## Applications

Safety transformer for the safe electrical isolation of the input and output sides. The transformer is suitable for creating SELV and PELV circuits because of the limit on the output voltage.

## Sample application



## Standards

Safety isolating transformer  
to: VDE 0570 Part 2-6, DIN EN 61558-2-6, EN 61558-2-6, IEC 61558-2-6,  
UL 5085-1/-2, CSA 22.2 No.66

## Approvals



VDE, UL 5085-1/-2, CSA 22.2 No.66



## Safety isolating transformer VR 7,5/1/18

Type		VR 7,5/1/18
Electrical data	Input	
	Rated input voltage	230 Vac
	Rated frequency	50 - 60 Hz
	Output	
	Rated output voltage	18 Vac
	Power	7.5 VA
	No-load voltage (app. x factor)	1.18
	No-load loss (typ.)	1.3 W
	Efficiency	76 %
	Standards	
	Classification	Safety isolating transformer
	Approvals	
	Approvals	cURus, VDE
	Environment	
	Ambient temperature max.	104.0 °F
Safety and protection		
Type	Encapsulated	
Insulation class	VDE=B, UL=class 105	
Protection index	IP 00	
Safety class (prepared)	II	
Short circuit strength	non-short-circuit proof	
Order numbers		
<b>Order Number</b>	<b>VR 7,5/1/18</b>	

Type		VR 7,5/1/18
Terminal and mounting	Terminal and mounting	
	Fixing method	Additional fixing by self-tapping screws
Terminals	Terminals	Pins for PCB
Measures and weights	Measures and weights	
	Pin (ø)	0.031 inch
	Core type	EI 48/16,8
Weight	Weight	0.62 lbs

