

# Safety isolating transformer PT 7,5/1/8



Picture shows PT 7,5/1/15

## Advantages


- Minimum size at high output
- Integrated overload protection using PTC in the input
- Dual output voltage for series or parallel connection
- Permanent corrosion protection, high insulation value and maximum electrical reliability due to XtraDenseFill resin encapsulation
- Self-extinguishing potting material
- Space saving installation due to additional screw mounting in the base plate

## Applications

As a mains transformer for adjustment of the voltage and simple electrical isolation.

Safety transformer for the safe electrical isolation of the input and output sides. The transformer is suitable for creating SELV and PELV circuits because of the limit on the output voltage.

## Sample application



## Standards

Safety isolating transformer  
to: VDE 0570 Part 2-6, DIN EN 61558-2-6, EN 61558-2-6, IEC 61558-2-6

## Approvals



VDE, UL 5085-1/-2, CSA 22.2 No.66



# Safety isolating transformer

## PT 7,5/1/8

Electrical data		Type	PT 7,5/1/8
Input			
Rated input voltage			230 Vac
Rated frequency			50 - 60 Hz
Output			
Rated output voltage			8 Vac
Power			7.5 VA
No-load voltage (app. x factor)			1.21
No-load loss (typ.)			1.3 W
Efficiency			65 %
Standards			
Classification			Safety isolating transformer
Approvals			
Approvals			cURus, VDE
Environment			
Ambient temperature max.			104.0 °F
Safety and protection			
Type			Encapsulated
Insulation class			VDE=E, UL=class 105
Protection index			IP 00
Safety class (prepared)			II
Short circuit strength			non-inherently short-circuit proof
Order numbers			
<b>Order Number</b>			<b>PT 7,5/1/8</b>

Mechanical data		Type	PT 7,5/1/8
Terminal and mounting			
Terminals			Pins for PCB
Measures and weights			
Pin (ø)			0.031 inch
Core type			EI 48/16,8
Weight			0.62 lbs

### Dimensions in inch

