

## Advantages

Minimum size at high power

Low weight

Dual input and dual output voltage for series or parallel connection

Minimal no-load losses

Outstanding temperature behavior due to low magnetic leakage field

Very low noise field


## Applications

As a mains transformer for adjustment of the voltage and simple electrical

As an isolating transformer for the safe electrical isolation of the input and output sides. The transformer may be used to set up protective separation as a protective measure in accordance with VDE 0100.

As a safety isolating transformer for the safe electrical isolation of the input and output sides. The transformer is suitable for creating SELV and PELV circuits because of the limit on the output voltage.

Sample application



Parallel connection: red with gresy/black with orange Series connection: black with grey

Series connection (230V): violet with white

## Standards

Safety isolating transformer to: VDE 0570 Part 2-6, DIN EN 61558-2-6, EN 61558-2-6, IEC 61558-2-6, UL 5085-1/-2, CSA 22.2 No.66

Approvals





UL 5085-1/-2, CSA 22.2 No.66



Picture shows RKD 60 2x12



## Safety isolating transformer **RKD 120/2x9**

Туре	RKD 120/2x9
Input	
Rated input voltage	2 x 115 Vac
Rated frequency	50 - 60 Hz
Output	
Rated output voltage	2 x 9 Vac
Power	120 VA
No-load voltage (app. x factor)	1.08
No-load loss (typ.)	1 W
Efficiency	91 %
Standards	
Classification	Safety isolating transformer
Approvals	
Approvals	cURus
Environment	
Ambient temperature max.	104.0 °F
Safety and protection	
Туре	Open type
Insulation class	VDE=B, UL=class 105
Insulation class Protection index	VDE=B, UL=class 105 IP 00
Protection index Safety class (prepared)	IP 00
Protection index Safety class (prepared) Short circuit strength	IP 00 II non-short-circuit proof
Protection index Safety class (prepared) Short circuit strength Test voltage	IP 00
Protection index Safety class (prepared) Short circuit strength	IP 00 II non-short-circuit proof
	Input Rated input voltage Rated frequency Output Rated output voltage Power No-load voltage (app. x factor) No-load loss (typ.) Efficiency Standards Classification Approvals Approvals Environment Ambient temperature max. Safety and protection

	Туре	RKD 120/2x9
00.	Terminal and mounting Fixing method	
~ <u>_</u>	Fixing method	Mounting kit, M6 bolt
	Terminals	Connecting leads, 200 mm
chanical data	Measures and weights	
q	Major diameter Ø	3.70 inch
Ö	Outside diameter in the area of the wire lead $\emptyset$	3.78 inch
÷	Height without mounting	1.81 inch
Эa	Weight	3.09 lbs
-		

