

Advantages

Minimum size at high output

Also with double output voltage for series or parallel connection

Permanent corrosion protection, high insulation value and maximum electrical reliability due to XtraDenseFill resin encapsulation


Self-extinguishing potting material

Space saving installation due to additional screw mounting in the base plate

Applications

Safety transformer for the safe electrical isolation of the input and output sides. The transformer is suitable for creating SELV and PELV circuits because of the limit on the output voltage.

Sample application



Standards

Safety isolating transformer to: VDE 0570 Part 2-6, DIN EN 61558-2-6, EN 61558-2-6, IEC 61558-2-6, UL 5085-1/-2, CSA 22.2 No.66

Approvals







VDE, UL 5085-1/-2, CSA 22.2 No.66





Safety isolating transformer **VR 13/2/9**

Type	VR 13/2/9	Туре	VR 13/2/9
Input		Terminal and mou	ınting
Rated input voltage	230 Vac	Fixing method	Additional fixing by self-tapping screws
Rated frequency	50 - 60 Hz	Terminals	Pins for PCB
Output Rated output voltage Power No-load voltage (app. x factor) No-load loss (typ.) Efficiency		Measures and we	eights
Rated output voltage	2 x 9 Vac	Pin (ø)	0.031 inch
Power	13 VA	Core type	EI 54/18,8
No-load voltage (app. x factor)	1.19	.⊖ Weight	0.93 lbs
No-load loss (typ.)	1.3 W	Core type Weight Dimensions in incl	
Efficiency	78 %	Dimensions in incl	h
Standards		Ž	48
Classification	Safety isolating transformer	1.18	
Approvals		1.10	0.1
Approvals	cURus, VDE		<u> </u>
Environment		1.18	
Ambient temperature max.	104.0 °F		0.79 0.2 2.2
Safety and protection		▼	0.2
Туре	Encapsulated		.85
Insulation class	VDE=B, UL=class 105	17 11	.00
Protection index	IP 00		
Safety class (prepared)	<u> </u>		
Short circuit strength	non-short-circuit proof		
Order numbers			
Order Number	VR 13/2/9		

